
PEARSON™ CURRENT MONITOR MODEL 8330

| | |
|--------------------------|--------------------------------|
| Sensitivity | 0.01 Volt/Ampere $\pm 1\%$ |
| Output resistance | 50 Ohms |
| Maximum peak current | 1,000 A for up to 1 ms / pulse |
| Maximum rms current | 100 Amperes |
| Drop rate | 0.1 % / microsecond |
| Useable rise time | 7 nanoseconds |
| Current time product | 0.3 Ampere-second maximum |
| Low frequency 3dB point | 200 Hz (approximate) |
| High frequency 3dB point | 50 MHz (approximate) |
| I/f figure | 1.5 RMS Amperes/Hz |
| Maximum DC current | 50 A |
| Output connector | BNC |
| Operating temperature | 0 to 65°C |
| Weight | 3.7 pounds |

